

Interconnector –Samand LX EF7 Petrol PTP Bosch ME17

| Engine | | | | IC02A 23W BK | | Front | | | |
|--------|-----------|---------|----------|------------------------|----------|---------|-----------|-------|------|
| Part | Connector | Pin Num | Wire Num | Interconnector Pin Num | Wire Num | Pin Num | Connector | Part | |
| 2200 | 2W GY | 2 | 220 | 1 | 220 | A2 | 13W BR | IC23B | |
| 1320A | 56W BK | A44 | 9019L | 2 | 9019 | 14 | 16W BK | C001 | |
| IC02A | 23W BK | 18 | 430 | 3 | 430 | B3 | 13W GY | IC23C | |
| 1320A | 56W BK | A3 | | | | | | | |
| 1320A | 56W BK | A12 | 432 | 5 | 432 | A7 | 13W GY | IC23C | |
| 1320A | 56W BK | A28 | 426 | 6 | 426 | 12 | 18W BK | 0004 | |
| 1320A | 56W BK | A29 | 435 | 7 | 435 | 14 | 18W BK | 0004 | |
| IC023 | 6W GY | 4 | 410 | 8 | 410 | 6 | 18W WI | 0004 | |
| 1020 | 2W BK | 1 | 1070 | 9 | 1070 | 16 | 16W BK | 8618 | |
| | | | | | | 16 | 18W WI | 0004 | |
| 1320A | 56W BK | A27 | 166 | 10 | 166 | 2 | 5W WI | 8208 | |
| 1320A | 56W BK | A30 | 405 | 11 | 405 | 14 | 18W WI | 0004 | |
| 8007 | 4W BR | 1 | C127 | 11 | C127 | B6 | 13W RD | BF00H | |
| 8007 | 4W BR | 4 | | | | | | | |
| 2200 | 2W GY | 1 | | | | | | | |
| 1127 | 5W YL | 2 | | | | | | | |
| 1203 | 3W BK | 1 | | | | | | | |
| 1320A | 56W BK | A16 | | | | | | | |
| | | | | 12 | | | | | |
| 1320A | 56W BK | A32 | 9020H | 13 | 9020 | 6 | 16W BK | C001 | |
| 1304 | 15W BK | 2 | 1500 | 14 | 1500 | 22 | 23W GY | IC01 | |
| 1304 | 15W BK | 6 | | | | | | | |
| 1304 | 15W BK | 13 | | | | | | | |
| C1320 | 2W BK | 1 | | | | | | | |
| IC02B | 23W BR | 1 | | | | | | | |
| 1350 | 4W BK | 1 | | | | | | | |
| 1351 | 4W GY | 1 | | | | | | | |
| 7113 | 2W BU | 2 | C820 | 15 | C820 | 3 | 5W WI | 8208 | |
| 1304 | 15W BK | 5 | | | | | | | |
| 1215 | 2W BK | 1 | | | | | | | |
| 1115 | 3W BK | 3 | | | | | | | |
| 1243 | 2W BK | 1 | | | | | | | |
| 1320A | 56W BK | A40 | | | | | | | 480 |
| C1260 | 2W BK | 1 | 121 | 17 | 121 | B2 | 13W GY | IC23C | |
| IC02A | 23W BK | 3 | 1837 | 18 | 1837 | A7 | 13W GY | IC24B | |
| 1320A | 56W BK | A3 | 1836 | 19 | 1836 | A6 | 13W GY | IC24B | |
| 1320A | 56W BK | A24 | 1836 | 20 | 1836 | 4 | 12W BK | 8618 | |
| 1320B | 56W BK | B32 | 1624 | 21 | 1624 | 11 | 18W BK | 0004 | |
| | | | | | | 28 | 38W BK | 7020 | |
| | | | | | | 13 | 18W BK | 0004 | |
| 1320B | 56W BK | B41 | 820 | 22 | 820 | 3 | 18W WI | 0004 | |
| 8020 | 2W WI | 1 | 8079 | 23 | 8079 | 5 | 5W GN | 8005 | |
| Engine | | | | IC02B 23W BR | | Front | | | |
| Part | Connector | Pin Num | Wire Num | Interconnector Pin Num | Wire Num | Pin Num | Connector | Part | |
| 1304 | 15W BK | 2 | C704 | 1 | C704 | 1 | 2W BR | 7045 | |
| 1304 | 15W BK | 6 | | | | | | | |
| 1304 | 15W BK | 13 | | | | | | | |
| C1320 | 2W BK | 1 | | | | | | | |
| IC02A | 23W BK | 14 | | | | | | | |
| 1350 | 4W BK | 1 | | | | | | | |
| 1351 | 4W GY | 1 | | | | | | | |
| 7113 | 2W BU | 2 | 1510 | 2 | 1510 | 11 | 23W GY | IC01 | |
| 1320A | 56W BK | A22 | | | | | | | |
| 1320B | 56W BK | B34 | | | | | | | 8091 |
| 1320A | 56W BK | A41 | 809 | 4 | 809 | 16 | 23W GY | IC01 | |
| | | | | 5 | | | | | |
| 1320A | 56W BK | A47 | 215 | 6 | 215 | 2 | 4W WI | 2100 | |
| | | | | | | 4B | 13W BR | IC23B | |
| 1320A | 56W BK | A35 | 218 | 7 | 218 | 30 | 38W BK | 7020 | |
| | | | | | | 4 | 4W WI | 2100 | |
| | | | | 8 | 1811 | A2 | 13W WI | IC20A | |
| | | | | 9 | 183 | B5 | 23W BR | IC23B | |
| | | | | 10 | 1810 | B6 | 13W WI | IC20A | |
| | | | | 11 | 1294 | 13 | 18W WI | 0004 | |
| 1320A | 56W BK | A39 | 141 | 12 | 1411 | 7 | 16W BK | C001 | |
| | | | | 13 | 184 | B6 | 13W WI | IC23B | |
| 1220 | 3W GY | 3 | 401 | 14 | 401 | 1 | 18W BK | 0004 | |
| 1010 | 1W | 1 | 1086 | 15 | 1086 | 4 | 5W GN | 1086 | |
| 1320A | 56W BK | A36 | 7045 | 16 | 7045 | 2 | 2W BR | 7045 | |
| 1320A | 56W BK | A6 | 1380 | 17 | 1380 | 5 | 6W BK | 1261 | |
| 1320A | 56W BK | A21 | 1379 | 18 | 1379 | 4 | 6W BK | 1261 | |
| 1320A | 56W BK | A11 | 1378 | 19 | 1378 | 6 | 6W BK | 1261 | |
| 1320A | 56W BK | A26 | 1376 | 20 | 1376 | 2 | 6W BK | 1261 | |
| 1320B | 56W BK | A38 | 1375 | 21 | 1375 | 1 | 6W BK | 1261 | |
| 1320A | 56W BK | A5 | 1374 | 22 | 1374 | 3 | 6W BK | 1261 | |
| 1320A | 56W BK | A31 | 8005 | 23 | 8005 | 2 | 5W GN | 8005 | |
| 1320A | 56W BK | A34 | 8055 | 23 | 8055 | 4 | 5W BK | 8005B | |



Interconnector –Samand LX EF7 Petrol PTP Bosch ME17

| Engine | | | | IC023 6W GY | Injector | | | |
|------------------|-----------|---------|----------|------------------------|----------|---------|-----------|--------|
| Part | Connector | Pin Num | Wire Num | Interconnector Pin Num | Wire Num | Pin Num | Connector | Part |
| 1320B | 56W BK | B44 | 1331 | 1 | 1331 | 2 | 2W BK | 1331 |
| 1320B | 56W BK | B42 | 1332 | 2 | 1332 | 2 | 2W BK | 1332 |
| 1304 | 15W BK | 4 | 1300A | 3 | 1200 | 1 | 2W BK | 1331 |
| | | | | | | 1 | 2W BK | 1332 |
| | | | | | | 1 | 2W BK | 1333 |
| | | | | | | 1 | 2W BK | 1334 |
| IC02A | 23W BK | 7 | 410 | 4 | 410 | 1 | 1W | 4110 |
| 1320B | 56W BK | B43 | 1333 | 5 | 1334 | 2 | 2W BK | 1333 |
| 1320B | 56W BK | B45 | 1334 | 6 | 1334 | 2 | 2W BK | 1334 |
| Engine | | | | IC024 6W BK | Coil | | | |
| Part | Connector | Pin Num | Wire Num | Interconnector Pin Num | Wire Num | Pin Num | Connector | Part |
| 1320B | 56W BK | B56 | 1131 | 1 | 1131 | 1 | 3W BK | 1131 |
| 1320B | 56W BK | B54 | 1133 | 2 | 1133 | 1 | 3W BK | 1133 |
| 8020 | 2W WI | 2 | E44 | 3 | E44 | 3 | 3W BK | 1131 |
| 2200 | 2W GY | 1 | | | | 3 | 3W BK | 1132 |
| 1320A | 56W BK | A53 | | | | 3 | 3W BK | 1133 |
| 1320A | 56W BK | A54 | | | | 3 | 3W BK | 1134 |
| E040 | | | | | | 3 | 3W BK | 1133 |
| 1313 | 3W BR | 3 | | | | 3 | 3W BK | 1134 |
| 1120 | 3W BK | 3 | | | | 3 | 3W BK | 1131 |
| 1262 | 8W BK | 7 | | | | 3 | 3W BK | 1132 |
| 1262 | 8W BK | 8 | 3 | 3W BK | 1133 | | | |
| 1127 | 5W YL | 3 | 1127 | 4 | 1220 | 2 | 3W BK | 1131 |
| | | | | | | 2 | 3W BK | 1132 |
| | | | | | | 2 | 3W BK | 1133 |
| | | | | | | 2 | 3W BK | 1134 |
| 1320B | 56W BK | B53 | 1132 | 5 | 1132 | 1 | 3W BK | 1132 |
| 1320B | 56W BK | B55 | 1134 | 6 | 1134 | 1 | 3W BK | 1134 |
| Instrument Panel | | | | IC20A 13W WI | Front | | | |
| Part | Connector | Pin Num | Wire Num | Interconnector Pin Num | Wire Num | Pin Num | Connector | Part |
| 6216 | 8W YL | 2 | 629 | 1A | 629 | 6A | 13W BK | IC21 |
| 1810 | 8W BU | 2 | 1811 | 2A | 1811 | 8 | 23W BR | IC02B |
| 6570 | 50W GN | 9 | 6220 | 3A | 6220 | 13 | 16W BK | C001 |
| 6570 | 50W GN | 12 | 475D | 5A | 475D | 6A | 13W GY | IC23C |
| | | | | | | 5 | 18W BK | 0004 |
| 6570 | 50W GN | 7 | 6560 | 6A | 6560 | 8 | 18W WI | 0004 |
| 6570 | 50W GN | 8 | 6561 | 7A | 6561 | 3 | 18W BK | 0004 |
| 3110 | 2W WI | 2 | A307 | 1B | A307 | A5 | 13W BR | BF00B |
| 7220 | 4W WI | 1 | B251 | 2B | B251 | A6 | 13W GY | BF00C |
| 7220 | 4W WI | 2 | A283 | 3B | A283 | B5 | 13W GY | BF00C |
| 6216 | 8W YL | 1 | A284 | | | | A2 | 13W GN |
| 7220 | 4W WI | 3 | VV6 | 4B | VV6 | A2 | 13W RD | BF00H |
| | | | | | | B3 | 5W WI | 0002 |
| | | | | | | 12 | 12W BK | 8618 |
| | | | | | | 7A | 13W BK | IC24A |
| 6570 | 50W GN | 21 | 623B | 5B | 623B | 2 | 12W BK | 8618 |
| | | | | | | 7A | 13W BK | IC22A |
| | | | | | | 5 | 9W BR | 6235 |
| 1810 | 8W BU | 1 | 1810 | 6B | 1810 | 9 | 23W BR | IC02B |
| 6570 | 50W GN | 5 | C06 | 7B | C06 | B1 | 13W RD | BF00H |

Interconnector –Samand LX EF7 Petrol PTP Bosch ME17

| Instrument Panel | | | | IC20B 13W BK | Front | | | |
|------------------|-----------|---------|----------|------------------------|----------|---------|-----------|-----------|
| Part | Connector | Pin Num | Wire Num | Interconnector Pin Num | Wire Num | Pin Num | Connector | Part |
| 2300 | 8W BK | 1 | 230 | 1A | 230 | 2 | 5W GY | 2305 |
| 2300 | 8W BK | 2 | A306 | 2A | A306 | B1 | 9W YL | BF00G |
| 2300 | 8W BK | 3 | B26 | 3A | B26 | A3 | 13W GN | BF00I |
| 2300 | 8W BK | 4 | 2330 | 5A | 2330 | A4 | 9W BK | 0002 |
| | | | | | | 1B | 8W BK | DB01 (D1) |
| | | | | | | 1 | 2W WI | 2340 |
| | | | | | | 1A | 13W BU | IC23A |
| 2300 | 8W BK | 5 | 2340 | 6A | 2340 | 7 | 23W GY | IC01 |
| | | | | | | 1 | 2W WI | 2345 |
| | | | | | | 1A | 13W GY | IC23C |
| | | | | | | 12 | 23W GY | IC01 |
| 2300 | 8W BK | 6 | 232 | 7A | 232 | 2B | 8W BK | DB01 (D2) |
| | | | | | | A2 | 9W BK | 0002 |
| 2300 | 8W BK | 8 | V19C | 1B | V19C | 5 | 5W GY | 2305 |
| | | | | | | 6 | 8W BK | 8410 |
| | | | | | | A6 | 11W WI | IC26A |
| | | | | | | B5 | 13W BU | BF00J |
| 8110 | 8W GN | 1 | K23 | 2B | K23 | 1 | 4W BR | 3050 |
| | | | | | | 810 | 810 | 3B |
| 8110 | 8W GN | 7 | V19 | 4B | V19E | 1B | 13W BK | IC20B |
| 6216 | 8W YL | 7 | | | | | | |
| 1810 | 8W BU | 7 | | | | | | |
| 8110 | 8W GN | 8 | 812 | 5B | 812 | 6A | 13W BK | IC24A |
| | | | | | | 5 | 5W OR | 8116 |
| | | | | | | 6A | 13W BK | IC22A |
| | | | | | | A7 | 13W BU | IC23A |
| 8100 | 3W BK | 1 | B16 | 6B | B16 | A7 | 13W BR | BF00B |
| 3053 | 1W BK | 1 | VR1 | 7B | VR1 | 1 | 4W BR | 3050 |
| 3054 | 2W WI | 1 | VR2 | | | 12 | 18W WI | 0004 |
| | | | | | | B2 | 11W WI | IC26A |
| Instrument Panel | | | | IC23E/IC23D 8W BU | Rear | | | |
| Part | Connector | Pin Num | Wire Num | Interconnector Pin Num | Wire Num | Pin Num | Connector | Part |
| 6570 | 50W GN | 13 | 650 | 1 | 650 | 1 | 2W YL | 6575 |
| 6570 | 50W GN | 14 | 651 | 2 | 651 | 2 | 2W YL | 6575 |
| 6570 | 50W GN | 16 | 652 | 3 | 652 | 1 | 2W YL | 6576 |
| 6570 | 50W GN | 17 | 653 | 4 | 653 | 2 | 2W YL | 6576 |
| | | | | 5 | | | | |
| | | | | 6 | | | | |
| | | | | 7 | | | | |
| | | | | 8 | | | | |



Interconnector – Samand LX EF7 Petrol PTP Bosch ME17

| Head Light (Front Panel) | | | | IC01 23W GY | Front | | | |
|--------------------------|-----------|---------|----------|------------------------|----------|---------|-----------|-----------|
| Part | Connector | Pin Num | Wire Num | Interconnector Pin Num | Wire Num | Pin Num | Connector | Part |
| | | | | 1 | | | | |
| | | | | 2 | | | | |
| 2615 | 6W BK | 1 | PC4 | | PC1 | 5B | 9W BK | 0002 |
| 2610 | 6W BK | 1 | PC3 | 3 | PC5 | 5 | 18W WI | 0004 |
| | | | | 4 | | | | |
| 2520A | 2W BK | 1 | 250 | | | | | |
| 2520B | 2W BK | 1 | 251 | 5 | 252 | A3 | 5W WI | 0002 |
| 2610 | 6W BK | 5 | V091 | | | | | |
| 2615 | 6W BK | 5 | V092 | 6 | V090 | B7 | 13W GY | BF00C |
| | | | | | | | | |
| 2610 | 6W BK | 6 | 2331 | 7 | 2331 | A4 | 9W BK | 0002 |
| | | | | | | 1B | 8W BK | DB01 (D1) |
| | | | | | | 1 | 2W WI | 2340 |
| | | | | | | 5A | 13W BK | IC20B |
| | | | | | | 1A | 13W BK | IC23A |
| | | | | 8 | | | | |
| 2615 | 6W BK | 2 | PR4 | | | | | |
| 2610 | 6W BK | 2 | PR3 | 9 | PR1 | B3 | 9W BK | 0002 |
| | | | | 10 | | | | |
| 1500B | 5W BK | 5 | | | | | | |
| 1500C | 5W BK | 4 | 1510 | 11 | 1510 | 2 | 23W BR | IC02B |
| 1510B | 2W BK | 1 | | | | | | |
| | | | | | | 1 | 2W WI | 2345 |
| | | | | | | 6A | 13W BK | IC20B |
| 2615 | 6W BK | 6 | 2341 | 12 | 2341 | 1A | 13W GY | IC23C |
| | | | | | | 2B | 8W BK | DB01 (D2) |
| | | | | | | A2 | 9W BK | 0002 |
| 2670 | 2W WI | 1 | PB6 | 13 | PB5 | 5 | 5W GN | 2665 |
| | | | | 14 | | | | |
| 1500B | 5W BK | 1 | 8091 | 15 | 8091 | 3 | 23W BR | IC02B |
| 1500A | 5W BK | 1 | 809 | 16 | 809 | 16 | 23W BR | IC02B |
| | | | | 17 | | | | |
| | | | | 18 | | | | |
| | | | | 19 | | | | |
| | | | | 20 | | | | |
| | | | | 21 | | | | |
| 1500B | 5W BK | 2 | C031 | 22 | 1500 | 14 | 23W BK | IC02A |
| | | | | 23 | | | | |
| Roof Lamp | | | | IC21 13W BK | Front | | | |
| Part | Connector | Pin Num | Wire Num | Interconnector Pin Num | Wire Num | Pin Num | Connector | Part |
| 8406 | 1W RD | 1 | 8401 | 1A | 8401 | 5 | 8W BK | 8410A |
| 3010 | 4W BK | 2 | | | | | | |
| 3010 | 4W BK | 3 | B153 | 2A | B153 | 7B | 13W GN | BF00I |
| 6230 | 8W BK | 7 | | | B15G | 4B | 13W GY | IC24B |
| | | | | | | 6A | 13W BR | IC23B |
| 3010 | 4W BK | 1 | 300 | 3A | 303 | 3 | 12W BK | 8616B |
| | | | | | | 3A | 8W WI | DB02 (D7) |
| | | | | | | | | |
| 3065 | 2W BR | 2 | | | | | | |
| 6230 | 8W BK | 8 | | | | | | |
| 3010 | 4W BK | 4 | EP | 5A | EP | 2B | 13W BK | IC24A |
| | | | | | | A4 | 11W WI | IC26A |
| 3060 | 2W WI | 2 | | | | B6 | 11W WI | IC26A |
| | | | | | | 6 | 12W BK | 8618 |
| 6230 | 8W BK | 3 | 629 | 6A | 629 | 1A | 13W WI | IC20A |
| 6230 | 8W BK | 4 | 6291 | 7A | 6291 | 1B | 13W GY | IC23C |
| | | | | | | 9 | 9W BR | 6235 |
| 6230 | 8W BK | 1 | 627 | 1B | 627 | 4 | 16W BK | 8618 |
| | | | | | | 6 | 9W BR | 6235 |
| 6230 | 8W BK | 2 | 628 | 2B | 628 | 5 | 16W BK | 8618 |
| | | | | | | | | |
| 3065 | 2W BR | 1 | A304 | 3B | A304 | 4B | 13W GN | BF00I |
| 3060 | 2W WI | 1 | A303 | | | | | |
| 6230 | 8W BK | 5 | 3033 | 4B | | | | |
| | | | | | | | | |
| 6230 | 8W BK | 6 | 6252A | 5B | 6252B | 8 | 9W BR | 6235 |
| | | | | | | 3 | 16W BK | 8618 |
| | | | | | | 1B | 13W BK | IC24A |
| | | | | 6B | | | | |
| | | | | 7B | | | | |

Interconnector – Samand LX EF7 Petrol PTP Bosch ME17

| FLH Door | | | | IC22A 13W BK | Front | | | |
|----------|-----------|---------|----------|------------------------|-----------------|---------|-----------|-----------|
| Part | Connector | Pin Num | Wire Num | Interconnector Pin Num | Wire Num | Pin Num | Connector | Part |
| IC25A | 13W BR | 6A | 841 | 1A | 8411 | 5 | 8W WI | 8410B |
| IC25A | 13W BR | 7A | 842 | 2A | 8421 | 6 | 8W WI | 8410B |
| 6240 | 2W BR | 1 | 6201 | 3A | 6201 | 3 | 9W BR | 6235 |
| | | | | | | 7A | 13W BR | IC23B |
| | | | | | | 3A | 13W BK | IC24A |
| 6240 | 2W BR | 2 | 6211 | 5A | 6211 | 4 | 9W BR | 6235 |
| | | | | | | 1B | 13W BR | IC23B |
| | | | | | | 5A | 13W BK | IC24A |
| 6410 | 5W WI | 4 | 813 | 6A | 813 | 6A | 13W BK | IC24A |
| | | | | | | 5 | 5W OR | 8116 |
| | | | | | | B5 | 13W BK | IC20B |
| 6200 | 3W WI | 2 | 6231 | 7A | 6231A | A7 | 13W BU | IC23A |
| | | | | | | 7A | 13W BK | IC24A |
| | | | | | | 2 | 12W BK | 8618 |
| 6200 | 3W WI | 1 | 6251 | 1B | 6251 | B5 | 13W WI | IC20A |
| | | | | | | 5 | 9W BR | 6235 |
| | | | | | | 7 | 9W BR | 6235 |
| IC25A | 13W BR | 5A | EPC | 2B | EPC | E020A | | |
| 6200 | 3W WI | 3 | | | | | | |
| 3000 | 2W BK | 1A | | | | | | |
| 6410 | 5W WI | 5 | | | | | | |
| IC25B | 13W GY | 1A | 606 | 3B | 606 | 3B | 13W BK | IC24A |
| IC25B | 13W GY | 3A | 607 | 4B | 607 | 4B | 13W BK | IC24A |
| IC25B | 13W GY | 2A | 6002 | 5B | 6005 | 5B | 13W BK | IC24A |
| | | | | | | 5 | 5W BK | 6020 |
| IC25B | 13W GY | 2B | A302 | 6B | A302 | 4B | 13W BR | BF00B |
| | | | | | | A301 | A5 | 13W GY |
| | | | | 7B | | | | |
| FLH Door | | | | IC22B 13W GY | Front | | | |
| Part | Connector | Pin Num | Wire Num | Interconnector Pin Num | Wire Num | Pin Num | Connector | Part |
| IC25A | 13W BR | 1A | 6411 | 1A | 6411 | 1A | 13W GY | IC24B |
| IC25A | 13W BR | 3B | 641 | 2A | 641 | 2A | 13W GY | IC24B |
| IC25A | 13W BR | 6B | 6412 | 3A | 6412 | 3A | 13W GY | IC24B |
| IC25A | 13W BR | 2B | A301 | 5A | A301 | 6B | 13W BK | IC22A |
| IC25B | 13W GY | 5B | 616 | 6A | 616 | B3 | 13W BU | IC23A |
| IC25B | 13W GY | 6B | 617 | 7A | 617 | B1 | 13W BU | IC23A |
| | | | | 1B | | | | |
| IC25B | 13W GY | 3B | 613 | 2B | 613 | B7 | 13W BU | IC23A |
| IC25B | 13W GY | 4B | 612 | 3B | 612 | B5 | 13W BU | IC23A |
| IC25B | 13W GY | 5A | 6111 | 4B | 6111 | B6 | 13W BU | IC23A |
| | | | | | | B2 | 13W BU | IC23A |
| IC25B | 13W GY | 6A | 6103 | 5B | 6103 | 5 | 5W BK | 6126 |
| 3000 | 2W BK | 1B | 3051 | 6B | 3051 | 4B | 8W BK | DB01 (D4) |
| 3040 | 2W WI | 2 | B15F | 7B | B15F | B6 | 13W GN | BF00I |
| FLH Door | | | | IC25A 13W BR | FLH Door Switch | | | |
| Part | Connector | Pin Num | Wire Num | Interconnector Pin Num | Wire Num | Pin Num | Connector | Part |
| IC22B | 13W GY | 1A | 6411 | 1A | 6411 | 3B | 8W BK | 6400 |
| | | | | 2A | | | | |
| | | | | 3A | | | | |
| IC22A | 13W BK | 2B | E001 | 5A | E001 | 2 | 5W WI | 6110 |
| 6200 | 3W WI | 3 | | | | 2 | 5W BK | 6115 |
| | | | | | | 3 | 5W GY | 6120 |
| | | | | | | 2A | 9W RD | 6030 |
| 3000 | 2W BK | 1A | 4 | 5W BK | 6115 | | | |
| | | | 4 | 5W WI | 6110 | | | |
| | | | 5 | 7W BU | 6000 | | | |
| 6410 | 5W WI | 5 | 2 | 5W BR | 6015 | | | |
| | | | 4 | 5W BR | 6015 | | | |
| | | | 4A | 8W BK | 6400 | | | |
| IC22A | 13W BK | 1A | 841 | 6A | 841 | 2 | 2W YL | 8420 |
| IC22A | 13W BK | 2A | 842 | 7A | 842 | 1 | 2W YL | 8420 |
| 6410 | 5W WI | 1 | 6401 | 1B | 6401 | 4B | 8W BK | 6400 |
| IC22B | 13W GY | 5A | A301 | 2B | A301 | 1A | 8W BK | 6400 |
| 6410 | 5W WI | 2 | 640 | 3B | 640 | 2A | 8W BK | 6400 |
| IC22B | 13W GY | 2A | 641 | | | 3A | 8W BK | 6400 |
| | | | | 4B | | | | |
| 6410 | 5W WI | 3 | 6402 | 5B | 6402 | 2B | 8W BK | 6400 |
| IC22B | 13W GY | 3A | 6412 | 6B | 6412 | 1B | 8W BK | 6400 |
| | | | | 7B | | | | |



Interconnector – Samand LX EF7 Petrol PTP Bosch ME17

| FLH Door | | | | IC25B 13W GY | FLH Door Switch | | | |
|----------|-----------|---------|----------|------------------------|-----------------|---------|-----------|-----------|
| Part | Connector | Pin Num | Wire Num | Interconnector Pin Num | Wire Num | Pin Num | Connector | Part |
| IC22A | 13W BK | 3B | 606 | 1A | 606 | 5 | 5W BR | 6015 |
| IC22A | 13W BK | 5B | 6002 | 2A | 6002 | 3 | 5W BR | 6015 |
| | | | | | 6005 | 5A | 9W RD | 6030 |
| IC22A | 13W BK | 4B | 607 | 3A | 607 | 1 | 5W BR | 6015 |
| IC22B | 13W GY | 4B | 6111 | 5A | 6111 | 2 | 5W GY | 6120 |
| IC22B | 13W GY | 5B | 6103 | 6A | 6103 | 1 | 5W GY | 6120 |
| 6040 | 2W GY | 2 | 6040 | 7A | 6040 | 1A | 9W RD | 6030 |
| | | | | 1B | | | | |
| IC22A | 13W BK | 6B | A302 | 2B | A302 | 3B | 9W RD | 6030 |
| IC22B | 13W GY | 2B | 613 | 3B | 613 | 1 | 5W WI | 6110 |
| IC22B | 13W GY | 3B | 612 | 4B | 612 | 5 | 5W WI | 6110 |
| IC22B | 13W GY | 6A | 616 | 5B | 616 | 5 | 5W BK | 6115 |
| IC22B | 13W GY | 7A | 617 | 6B | 617 | 1 | 5W BK | 6115 |
| 6040 | 2W GY | 1 | 6050 | 7B | 6050 | 4A | 9W RD | 6030 |
| FRH Door | | | | IC24A 13W BK | Front | | | |
| Part | Connector | Pin Num | Wire Num | Interconnector Pin Num | Wire Num | Pin Num | Connector | Part |
| 8425 | 2W YL | 2 | 843 | 1A | 8431 | 3 | 8W WI | 8410B |
| 8425 | 2W YL | 1 | 844 | 2A | 8441 | 4 | 8W WI | 8410B |
| | | | | | | 3 | 9W BR | 6235 |
| 6245 | 2W BR | 1 | 6202 | 3A | 6202 | 3A | 13W BK | IC22A |
| | | | | | | 7A | 13W BR | IC23B |
| | | | | | | 4 | 9W BR | 6235 |
| 6245 | 2W BR | 2 | 6212 | 5A | 6212 | 5A | 13W BK | IC22A |
| | | | | | | 1B | 13W BR | IC23B |
| | | | | | | 7A | 13W BK | IC23A |
| 6415 | 10W BK | 4 | 814 | 6A | 814 | 5 | 5W OR | 8116 |
| | | | | | | 6A | 13W BK | IC22A |
| | | | | | | 5B | 13W BK | IC20B |
| | | | | | | 5B | 13W WI | IC20A |
| 6205 | 3W WI | 2 | 6232 | 7A | 6231 | 2 | 12W BK | 8618 |
| | | | | | | 7A | 13W BK | IC22A |
| | | | | | | 5 | 9W BR | 6235 |
| 6205 | 3W WI | 1 | 6252 | 1B | 6252 | 8 | 9W BR | 6235 |
| | | | | | | 3 | 16W BK | 8618 |
| | | | | | | 5B | 13W BK | IC21 |
| 6205 | 3W WI | 3 | E620 | 2B | E814 | E020 | | |
| | | | | | | 5A | 13W BK | IC21 |
| | | | | | | A4 | 11W WI | IC26A |
| 6415 | 10W BK | 5 | E814 | | | B6 | 11W WI | IC26A |
| | | | | | | 6 | 12W BK | 8618 |
| 6005 | 5W BR | 4 | 606 | 3B | 606 | 3B | 13W BK | IC22A |
| 6005 | 5W BR | 2 | 607 | 4B | 607 | 4B | 13W BK | IC22A |
| 6005 | 5W BR | 3 | 6003 | 5B | 6003 | 5B | 13W BK | IC22A |
| | | | | 6B | | 5 | 5W BK | 6020 |
| | | | | 7B | | | | |
| FRH Door | | | | IC24B 13W GY | Front | | | |
| Part | Connector | Pin Num | Wire Num | Interconnector Pin Num | Wire Num | Pin Num | Connector | Part |
| 6415 | 10W BK | 1 | 6411 | 1A | 6411 | 1A | 13W GY | IC22B |
| 6415 | 10W BK | 2 | 641 | 2A | 641 | 2A | 13W GY | IC22B |
| 6415 | 10W BK | 3 | 6412 | 3A | 6412 | 3A | 13W GY | IC22B |
| | | | | 5A | | | | |
| 6415 | 10W BK | 10 | 1836 | 6A | 1836 | 19 | 23W BK | IC02A |
| 6415 | 10W BK | 9 | 1837 | 7A | 1837 | 18 | 23W BK | IC02A |
| | | | | 1B | | | | |
| | | | | 2B | | | | |
| 3001 | 2W BK | 1B | 3061 | 3B | 3045 | 3B | 8W BK | DB01 (D3) |
| 3045 | 2W WI | 2 | B15G | 4B | B15G | 2A | 13W BK | IC21 |
| | | | | 5B | | | | |
| | | | | 6B | | | | |
| | | | | 7B | | | | |



Interconnector – Samand LX EF7 Petrol PTP Bosch ME17

| RLH Door | | | | IC32 9W BR | Rear | | | |
|----------|-----------|---------|----------|------------------------|----------|---------|-----------|-----------|
| Part | Connector | Pin Num | Wire Num | Interconnector Pin Num | Wire Num | Pin Num | Connector | Part |
| 3042 | 2W WI | 1 | 3042 | 1A | 3042 | 1B | 2W BK | 3002 |
| 3042 | 2W WI | 2 | B15D | 2A | B15D | 2 | 4W BK | 3020 |
| | | | | | | 1 | 1W | 3105A |
| | | | | | | 2A | 9W BR | IC33 |
| | | | | | | 1A | 13W BR | IC23B |
| 6250 | 2W BR | 1 | 6209 | 4A | 6203 | 4A | 9W BR | IC33 |
| | | | | | | 2 | 2W WI | 6265 |
| | | | | | | 7A | 13W BR | IC23B |
| | | | | | | 4A | 9W BR | IC60 |
| 6250 | 2W BR | 2 | 6213 | 5A | 6213 | 5A | 9W BR | IC33 |
| | | | | | | 1 | 2W WI | 6265 |
| | | | | | | 1B | 13W BR | IC23B |
| | | | | | | 5A | 9W BR | IC60 |
| 6100 | 5W RD | 4 | 612 | 1B | 612 | 5B | 13W BU | IC23A |
| 6100 | 5W RD | 3 | 6111 | 2B | 6111 | 6B | 13W BU | IC23A |
| 6100 | 5W RD | 2 | 613 | 3B | 613 | 7B | 13W BU | IC23A |
| | | | | 4B | | | | |
| | | | | 5B | | | | |
| RRH Door | | | | IC33 9W BR | Rear | | | |
| Part | Connector | Pin Num | Wire Num | Interconnector Pin Num | Wire Num | Pin Num | Connector | Part |
| 3047 | 2W WI | 1 | 3043 | 1A | 3043 | 1B | 2W BK | 3003 |
| 3047 | 2W WI | 2 | B15E | 2A | B15E | 2 | 4W BK | 3020 |
| | | | | | | 1 | 1W | 3105A |
| | | | | | | 2A | 9W BR | IC32 |
| | | | | | | 1A | 13W BR | IC23B |
| 6255 | 2W BR | 1 | 6204 | 4A | 6204 | 4A | 9W BR | IC32 |
| | | | | | | 2 | 2W WI | 6265 |
| | | | | | | 7A | 13W BR | IC23B |
| | | | | | | 4A | 9W BR | IC60 |
| 6255 | 2W BR | 2 | 6214 | 5A | 6214 | 5A | 9W BR | IC32 |
| | | | | | | 1 | 2W WI | 6265 |
| | | | | | | 1B | 13W BR | IC23B |
| | | | | | | 5A | 9W BR | IC60 |
| 6105 | 5W RD | 2 | 617 | 1B | 617 | 1B | 13W BU | IC23A |
| 6105 | 5W RD | 3 | 6112 | 2B | 6112 | 2B | 13W BU | IC23A |
| 6105 | 5W RD | 4 | 616 | 3B | 616 | 3B | 13W BU | IC23A |
| | | | | 4B | | | | |
| | | | | 5B | | | | |
| Rear | | | | IC23A 13W BK | Front | | | |
| Part | Connector | Pin Num | Wire Num | Interconnector Pin Num | Wire Num | Pin Num | Connector | Part |
| 2630 | 6W BR | 2 | 2333 | 1A | 2333 | A4 | 9W BK | 0002 |
| | | | | | | 1B | 8W BK | DB01 (D1) |
| | | | | | | 1 | 2W WI | 2340 |
| | | | | | | 5A | 13W BK | IC20B |
| | | | | | | 7 | 23W GY | IC01 |
| IC60 | 9W BR | 4B | V09 | 2A | V09 | 2B | 13W GN | BF00I |
| 8430 | 2W YL | 1 | 846 | 3A | 846 | 8 | 8W WI | 8410B |
| 8430 | 2W YL | 2 | 845 | 5A | 845 | 7 | 8W WI | 8410B |
| IC6302 | 2W RD | 1 | K20A | 6A | K20 | A1 | 13W GN | BF00I |
| IC6303 | 2W RD | 1 | K20B | | | | | |
| 8120A | 1W BK | 1 | 811 | 7A | 811 | 6A | 13W BK | IC24A |
| | | | | | | 5 | 5W OR | 8116 |
| | | | | | | 6A | 13W BK | IC22A |
| | | | | | | 5B | 13W BK | IC20B |
| IC33 | 9W BR | 1B | 617 | 1B | 617 | A7 | 13W GY | IC22B |
| IC33 | 9W BR | 2B | 6112 | 2B | 6112 | B4 | 13W GY | IC22B |
| IC33 | 9W BR | 3B | 616 | 3B | 616 | A6 | 13W GY | IC22B |
| | | | | 4B | | | | |
| IC32 | 9W BR | 1B | 612 | 5B | 612 | B3 | 13W GY | IC22B |
| IC32 | 9W BR | 2B | 6111 | 6B | 6111 | B4 | 13W GY | IC22B |
| IC32 | 9W BR | 3B | 613 | 7B | 613 | B2 | 13W GY | IC22B |

Interconnector –Samand LX EF7 Petrol PTP Bosch ME17

| Rear | | | | IC23B 13W BR | Front | | | | | | |
|-------|-----------|---------|----------|------------------------|----------|---------|-----------|-----------|-------|--------|-----------|
| Part | Connector | Pin Num | Wire Num | Interconnector Pin Num | Wire Num | Pin Num | Connector | Part | | | |
| 3020 | 4W BK | 2 | B154 | 1A | B154 | 6B | 13W GN | BF00I | | | |
| 3105A | 1W | 1 | | | | | | | | | |
| IC32 | 9W BR | 2A | | | | | | | | | |
| IC33 | 9W BR | 2A | | | | | | | | | |
| IC220 | 8W WI | 1 | 220 | 2A | 220 | 1 | 23W BK | IC02A | | | |
| 2225 | 2W WI | 1 | | | | | | | | | |
| IC60 | 9W BR | 2B | | | | | | | | | |
| D01 | 2W | A | | | | | | | | | |
| D02 | 2W | A | 307 | 3A | 307 | 3A | 8W BK | DB01 (D3) | | | |
| IC60 | 9W BR | 1B | 308 | | | | | | | | |
| | | | 202 | | | | | | | | |
| | | | | | | | | | | | |
| 3020 | 4W BK | 1 | 301 | 6A | 301 | 1B | 13W GN | BF00I | | | |
| IC32 | 9W BR | 4A | | | | | | | | | |
| 6265 | 2W WI | 2 | | | | | | | | | |
| IC33 | 9W BR | 4A | | | | | | | | | |
| IC60 | 9W BR | 4A | 6208 | 7A | 6208 | 3A | 12W BK | 8616B | | | |
| IC32 | 9W BR | 5A | | | | | | | | | |
| 6265 | 2W WI | 1 | | | | | | | | | |
| IC33 | 9W BR | 5A | | | | | | | | | |
| IC60 | 9W BR | 5A | 6218 | 1B | 6218 | 3A | 9W BR | 6235 | | | |
| IC32 | 9W BR | 5A | | | | | | | | | |
| 6265 | 2W WI | 1 | | | | | | | | | |
| IC33 | 9W BR | 5A | | | | | | | | | |
| 3100 | 2W BR | 1 | 8618 | 2B | 8616 | 1B | 8W WI | DB02 (D5) | | | |
| | | | | | | | | | 8616A | | |
| | | | | | | | | | | | |
| | | | | | | | | | | | |
| 4400 | 2W BR | 1 | 440 | 3B | 440 | 12 | 16W BK | 8618 | | | |
| | | | | | | | | | | | |
| | | | | | | | | | | | |
| | | | | | | | | | | | |
| 2110 | 2W WI | 2 | 210 | 4B | 210 | 15 | 18W WI | 0004 | | | |
| 2630 | 6W BR | 5 | | | | | | | | | |
| 2635 | 6W BR | 2 | | | | | | | | | |
| 1803A | 2W BK | 1 | | | | | | | | | |
| 1803A | 2W BK | 2 | 1803 | 5B | 183 | 9 | 23W BR | IC02B | | | |
| | | | | | | | | | | | |
| | | | | | | | | | | | |
| | | | | | | | | | | | |
| | | | 1804 | 6B | 184 | 12 | 23W BR | IC02B | | | |
| | | | | | | | | | | | |
| | | | | | | | | | | | |
| | | | | | | | | | | | |
| | | | E027 | 7B | E841 | 8 | 8W BK | 8410A | | | |
| | | | E841 | | | | | | | | |
| | | | | | | | | | | | |
| | | | | | | | | | | | |
| Rear | | | | IC23C 13W GY | Front | | | | | | |
| Part | Connector | Pin Num | Wire Num | Interconnector Pin Num | Wire Num | Pin Num | Connector | Part | | | |
| 2635 | 6W BR | 2 | 2343 | 1A | 2345 | 1 | 2W WI | 2345 | | | |
| | | | | | | | | | 6A | 13W BK | IC20B |
| | | | | | | | | | 12 | 23W GY | IC01 |
| | | | | | | | | | 2B | 8W BK | DB01 (D2) |
| | | | | | | A2 | 9W BK | 0002 | | | |
| 2635 | 6W BR | 6 | V04 | 2A | V04 | 1B | 13W BU | BF00J | | | |
| 8435 | 2W YL | 1 | 848 | 3A | 848 | 2 | 8W WI | 8410B | | | |
| 8435 | 2W YL | 2 | 847 | 5A | 847 | 1 | 8W WI | 8410B | | | |
| 4730 | 2W WI | 2 | 475 | 6A | 475 | 5 | 18W BK | 0004 | | | |
| | | | | | | A5 | 13W WI | IC20A | | | |
| 4310 | 6W BK | 6 | 432 | 7A | 432 | 4 | 23W BK | IC02A | | | |
| IC60 | 9W BR | 1A | 6291 | 1B | 6291 | A7 | 13W BK | IC21 | | | |
| 4310 | 6W BK | 3 | 121 | 2B | 121 | 17 | 23W BK | IC02A | | | |
| 4310 | 6W BK | 1 | 430 | 3B | 430 | 3 | 23W BK | IC02A | | | |
| 7010 | 2W BK | 1 | 702 | 4B | 702 | 20 | 38W BK | 7020 | | | |
| 7015 | 2W BK | 1 | 703 | 5B | 703 | 31 | 38W BK | 7020 | | | |
| 7015 | 2W BK | 2 | 7031 | 6B | 7031 | 19 | 38W BK | 7020 | | | |
| 7010 | 2W BK | 2 | 7021 | 7B | 7021 | 33 | 38W BK | 7020 | | | |



Interconnector – Samand LX EF7 Petrol PTP Bosch ME17

| Rear | | | | IC60 9W BR | Boot Lid | | | | | | |
|--------|-----------|---------|----------|------------------------|---------------|---------|-----------|-------|-------|-------|--|
| Part | Connector | Pin Num | Wire Num | Interconnector Pin Num | Wire Num | Pin Num | Connector | Part | | | |
| IC23C | 13W GY | 1B | 6291 | 1A | 6291 | 2 | 2W BR | 6260 | | | |
| | | | | 2A | | | | | | | |
| IC32 | 9W BR | 4A | 6206 | 4A | | | | | | | |
| 6265 | 2W WI | 2 | | | | | | | | | |
| IC33 | 9W BR | 4A | | | | | | | | | |
| IC23B | 13W BR | 7A | | | | | | | | | |
| IC32 | 9W BR | 5A | 6216 | 5A | | | | | | | |
| 6265 | 2W WI | 1 | | | | | | | | | |
| IC33 | 9W BR | 5A | | | | | | | | | |
| IC23B | 13W BR | 1B | | | | | | | | | |
| IC23B | 13W BR | 5A | 202 | 1B | 202 | 4 | 6W BR | 2632 | | | |
| | | | | | 203 | 4 | 6W BR | 2637 | | | |
| IC220 | 8W WI | 1 | 222 | 2B | 220 | 3 | 6W BR | 2632 | | | |
| 2225 | 2W WI | 1 | | | | | 221 | 3 | 6W BR | 2637 | |
| IC23B | 13W BR | 2A | | | | | | | | | |
| 3002 | 2W BK | 1A | E26C | 3B | E26C | 1 | 2W BR | 6260 | | | |
| 3020 | 4W BK | 4 | | | | | | 1 | 6W BR | 6232 | |
| 3100 | 2W BR | 2 | | | | | | 1 | 6W BR | 6237 | |
| 2110 | 2W WI | 1 | | | | | | 1 | 2W WI | 6236 | |
| IC220 | 8W WI | 2 | | | | | | | | | |
| 2630 | 6W BR | 1 | | | | | | | | | |
| | E026G | | | | | | | | | | |
| IC23A | 13W BU | 2A | V09 | 4B | V094 | 2 | 2W WI | 2636 | | | |
| 2630 | 6W BR | 1 | V094 | | | | | | | | |
| | | | | 5B | | | | | | | |
| Rear | | | | IC220 8W WI | Rear Bumper | | | | | | |
| Part | Connector | Pin Num | Wire Num | Interconnector Pin Num | Wire Num | Pin Num | Connector | Part | | | |
| IC60 | 9W BR | 2B | 2201 | 1 | 220 | B2 | 4W BK | 2200A | | | |
| 2225 | 2W WI | 1 | | | | | | B2 | 4W BK | 2205 | |
| IC23B | 13W BR | 2A | E2201 | 2 | E220 | A1 | 4W BK | 2200A | | | |
| 3002 | 2W BK | 1A | | | | | | D4 | 4W BK | 2200A | |
| 3020 | 4W BK | 4 | | | | | | | | | |
| 3100 | 2W BR | 2 | | | | | | D4 | 4W BK | 2205 | |
| 2110 | 2W WI | 1 | | | | | | | | | |
| IC60 | 9W BR | 3B | | | | | | | | | |
| 2630 | 6W BR | 1 | | | | | | | | | |
| | E026G | | | | | | | | | | |
| 2225 | 2W WI | 2 | 227 | 3 | 2091 | C3 | 4W BK | 2205 | | | |
| | | | | 4 | | | | | | | |
| | | | | 5 | | | | | | | |
| | | | | 6 | | | | | | | |
| | | | | 7 | | | | | | | |
| | | | | 8 | | | | | | | |
| Rear | | | | IC6302 2W RD | LH Power Seat | | | | | | |
| Part | Connector | Pin Num | Wire Num | Interconnector Pin Num | Wire Num | Pin Num | Connector | Part | | | |
| IC23A | 13W BU | 6A | K02A | 1 | K20 | 3 | 5W BR | 6340 | | | |
| | E027 | | | | | | | | | | |
| IC6303 | 2W RD | 2 | E63B | 2 | E630 | 2 | 5W BR | 6340 | | | |
| 4730 | 2W WI | 1 | | | | | | | | | |
| 4400 | 2W BR | 2 | | | | | | | | | |
| 4310 | 6W BK | 4 | | | | | | | | | |
| Rear | | | | IC6303 2W RD | RH Power Seat | | | | | | |
| Part | Connector | Pin Num | Wire Num | Interconnector Pin Num | Wire Num | Pin Num | Connector | Part | | | |
| IC23A | 13W BU | 6A | K20B | 1 | K20 | 3 | 5W BR | 6345 | | | |
| | E027 | | | | | | | | | | |
| IC6302 | 2W RD | 2 | E63A | 2 | E630 | 2 | 5W BR | 6345 | | | |
| 4730 | 2W WI | 1 | | | | | | | | | |
| 4400 | 2W BR | 2 | | | | | | | | | |
| 4310 | 6W BK | 4 | | | | | | | | | |

Interconnector –Samand LX EF7 Petrol PTP Bosch ME17

| Air Condition | | | | IC26A 11W WI | Front | | | |
|---------------|-----------|---------|----------|------------------------|----------|---------|-----------|-------|
| Part | Connector | Pin Num | Wire Num | Interconnector Pin Num | Wire Num | Pin Num | Connector | Part |
| 8050 | 2W | 1 | 803A | 1A | 803A | 3 | 5W YL | 8048 |
| 8015C | 5W | 1 | | | | 5B | 11W WI | IC26A |
| 8070 | 5W | 2 | K05 | 2A | K05 | 1A | 13W RD | BF00H |
| 8025 | 10W | 8 | | | | | | |
| 8047 | 6W | 5 | E051 | 4A | E051 | E020 | | |
| 8015C | 5W | 4 | | | | 5A | 13W BK | IC21 |
| | | | | | | B2 | 13W BK | IC24A |
| | | | | | | B6 | 11W WI | IC26A |
| | | | 6 | 12W BK | 8618 | | | |
| 8006 | 2W BK | 1 | E80 | 5A | E80 | E006 | | |
| 8035 | 7W | 7 | | | | 4 | 4W BR | 8605 |
| 8025 | 10W | 5 | | | | 4 | 7W BR | 7025 |
| 8025 | 10W | 10 | V19T | 6A | V19T | 6 | 8W BK | 8410A |
| | | | | | | B1 | 13W BK | IC20B |
| | | | | | | B5 | 13W BU | BF00J |
| | | | | | | 1 | 4W BR | 3050 |
| 8035 | 7W | 1 | C02C | 1B | C02C | 3 | 5W GN | 8005 |
| 8015B | 5W | 1 | | | | A6 | 13W RD | BF00H |
| 8015B | 5W | 4 | | | | | | |
| 8025 | 10W | 3 | VR2 | 2B | VR2 | 1 | 4W BR | 3050 |
| | | | | | | 12 | 18W WI | 0004 |
| | | | | | | 7B | 13W BK | IC20B |
| 8015A | 5W | 3 | 8054 | 3B | 8054 | 3 | 5W BK | 8005B |
| | | | | | 8053 | 10 | 16W BK | 8618 |
| 8015A | 5W | 2 | 803B | 4B | | | | |
| 8025 | 10W | 2 | | | | | | |
| | | | | 5B | 803B | 3 | 5W YL | 8048 |
| | | | | | | 1A | 11W WI | IC26A |
| | | | | 6B | E052 | E020 | | |
| | | | | | | 5A | 13W BK | IC21 |
| | | | | | | A4 | 11W WI | IC26A |
| | | | | | | B2 | 13W BK | IC24A |
| | | | | | | 6 | 12W BK | 8618 |